IN THE CLAIMS:

1. (CURRENTLY AMENDED) A system configured to acknowledge and service an interrupt issued to a processor of an intermediate node, the system comprising:

an external device coupled to a high latency path, the external device generating a pulsed interrupt signal for each type of interrupt supported by the processor;

an interrupt multiplexing device accessible by the processor over a fast bus;~~, the interrupt multiplexing device adapted to issue the interrupt to the processor in response to each pulsed interrupt signal generated by the external device;~~

a low latency path coupling the external device to the interrupt multiplexing device and adapted to transport each pulsed interrupt signal generated by the external device to the interrupt multiplexing device; and

a status bit stored within the interrupt multiplexing device, the status bit adapted for assertion whenever the pulsed interrupt signal is detected at the interrupt multiplexing device,

wherein, in response to the pulsed interrupt signal, the interrupt multiplexing device issues a level sensitive interrupt (LSI) signal to the processor over the fast bus, the LSI signal remaining asserted until the interrupt is acknowledged by the processor by clearing the status bit.~~the processor acknowledges the issued interrupt without accessing the high latency path by accessing the interrupt multiplexing device over the fast bus.~~

2. (ORIGINAL) The system of Claim 1 further comprising a current counter associated with the interrupt multiplexing device, the current counter incremented in response to each pulsed interrupt signal at the interrupt multiplexing device.

3. (ORIGINAL) The system of Claim 2 further comprising an interrupt handler invoked by the processor to service the issued interrupt.

4. (ORIGINAL) The system of Claim 3 further comprising a last counter associated with the processor, the last counter incremented in response to each interrupt serviced by the CPU.

5. (ORIGINAL) The system of Claim 4 further comprising means for comparing a value of the last counter with a value of the current counter to determine whether there are more interrupts to service.

6. (ORIGINAL) The system of Claim 5 wherein the means for comparing comprises the interrupt handler.

7. (ORIGINAL) The system of Claim 1 wherein the external device is a direct memory access controller.

8. (ORIGINAL) The system of Claim 1 wherein the low latency path is a printed circuit board trace.

9. (ORIGINAL) The system of Claim 1 wherein the high latency path is a peripheral computer interconnect bus.

10. (ORIGINAL) The system of Claim 1 wherein the interrupt multiplexing device is a field programmable gate array device.

11. (CURRENTLY AMENDED) A method for acknowledging and servicing an interrupt issued to a processor of an intermediate node, the method comprising the steps of:

generating a pulsed interrupt signal at an external device coupled to a high latency path;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a low latency path coupling the external device to the interrupt multiplexing device;

asserting a status bit in response to detecting the pulsed interrupt signal at the interrupt multiplexing device;

issuing a level sensitive interrupt (LSI) signal ~~the interrupt~~ to the processor in response to each pulsed interrupt signal received at the interrupt multiplexing device, the LSI signal remaining asserted until the interrupt is acknowledged by the processor; and

invoking an interrupt handler to service the issued interrupt;

acknowledging the interrupt by by clearing the status bit in~~accessing~~ the interrupt multiplexing device.

12. (PREVIOUSLY PRESENTED) The method of Claim 11 further comprising the steps of:

initializing a last counter; and

incrementing the last counter in response to each interrupt serviced.

13. (ORIGINAL) The method of Claim 12 further comprising the steps of:

reading the status bit; and

if the status bit is clear, dismissing the handler.

14. (ORIGINAL) The method of Claim 13 wherein the step of reading further comprises the step of clearing the status bit.

15. (PREVIOUSLY PRESENTED) The method of Claim 13 further comprising the steps of:

incrementing a current counter in response to each pulsed interrupt signal at the interrupt multiplexing device;

if the status bit is set, reading a value of the current counter;

comparing the current counter value with a value of the last counter; and

if the last counter value is greater than or equal to the current counter value, returning to the step of reading the status bit.

16. (ORIGINAL) The method of Claim 15 further comprising the steps of:

if the last counter value is not greater than or equal to the current counter value, checking a control block stored in a memory of the node, the control block shared between the processor and the external device; and

determining whether the processor owns the control block.

17. (ORIGINAL) The method of Claim 16 further comprising the steps of:

if the processor owns the control block, processing the control block; and

incrementing the last counter.

18. (ORIGINAL) The method of Claim 17 further comprising the steps of:

determining whether a preset limit for processing control blocks has been reached; and

if the preset limit is reached, dismissing the handler.

19. (CURRENTLY AMENDED) Apparatus for acknowledging and servicing an interrupt issued to a processor of an intermediate node, the apparatus comprising:

means for generating a pulsed interrupt signal at an external device coupled to a high latency path;

means for transporting the pulsed interrupt signal to an interrupt multiplexing device over a low latency path coupling the external device to the interrupt multiplexing device;

means for asserting a status bit in response to detecting the pulsed interrupt signal at the interrupt multiplexing device;

means for issuing a level sensitive interrupt (LSI) signal ~~the interrupt~~ to the processor in response to each pulsed interrupt signal received at the interrupt multiplexing device, the LSI signal remaining asserted until the interrupt is acknowledged by the processor; and

means for invoking an interrupt handler to service the issued interrupt;

means for acknowledging the interrupt by ~~accessing~~ by clearing the status bit in the interrupt multiplexing device.

20. (CURRENTLY AMENDED) A computer readable medium containing executable program instructions for acknowledging and servicing an interrupt issued to a processor of an intermediate node, the executable program instructions comprising program instructions for:

generating a pulsed interrupt signal at an external device coupled to a high latency path;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a low latency path coupling the external device to the interrupt multiplexing device;

asserting a status bit in response to detecting the pulsed interrupt signal at the interrupt multiplexing device;

issuing a level sensitive interrupt (LSI)~~the interrupt~~ to the processor in response to each pulsed interrupt signal received at the interrupt multiplexing device, the LSI signal remaining asserted until the interrupt is acknowledged by the processor; and

invoking an interrupt handler to service the issued interrupt;

acknowledging the interrupt by ~~accessing~~ by clearing the status bit in the interrupt multiplexing device.

21. (CURRENTLY AMENDED) Electromagnetic signals propagating on a computer network comprising,

the electromagnetic signals carrying instructions for execution on a processor for:

generating a pulsed interrupt signal at an external device coupled to a high latency path;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a low latency path coupling the external device to the interrupt multiplexing device;

asserting a status bit in response to detecting the pulsed interrupt signal at the interrupt multiplexing device;

issuing a level sensitive interrupt (LSI) ~~the interrupt~~ to the processor in response to each pulsed interrupt signal received at the interrupt multiplexing device, the LSI signal remaining asserted until the interrupt is acknowledged by the processor; and

invoking an interrupt handler to service the issued interrupt

acknowledging the interrupt by ~~accessing~~ by clearing the status bit in the interrupt multiplexing device.

22. (CURRENTLY AMENDED) A method for acknowledging and servicing an interrupt issued to a processor, the method comprising:

generating a pulsed interrupt signal at an external device;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a first low latency path that couples the external device to the interrupt multiplexing device;

asserting a status bit in the interrupt multiplexing device corresponding to the interrupt in response to detecting the pulsed interrupt signal;

issuing ~~the interrupt~~ to the processor over a second low latency path, in response to the pulsed interrupt signal, a level sensitive interrupt (LSI) signal, the LSI signal remaining asserted until the interrupt is acknowledged by the processor;

reading the status bit over the second low latency path by an interrupt handler internal to the processor; and

clearing the status bit in response to the reading of the status bit to effectively acknowledge the interrupt.

23. (PREVIOUSLY PRESENTED) The method of claim 22 further comprising:

checking, by the interrupt handler, ownership of a control block and in response to the processor owning the control block, processing the control block.

24. (PREVIOUSLY PRESENTED) The method of claim 23 further comprising:

assigning ownership of the control block over a high latency path.

25. (PREVIOUSLY PRESENTED) The method of claim 23 further comprising:

incrementing a current counter in response to each pulsed interrupt signal received at the interrupt multiplexing device;

incrementing a last counter in response each control block processed by the interrupt handler;

comparing the value of the current counter and the value of the last counter; and

if the value of the current counter is greater than the value of the last counter, which thereby indicates the control block corresponding to the interrupt has not yet been processed, continuing to attempt to access and process the control block.

26. (PREVIOUSLY PRESENTED) The method of Claim 25 further comprising:

determining whether a preset limit for processing control blocks has been reached; and

if the preset limit is reached, dismissing the interrupt handler.

27. (CURRENTLY AMENDED) An apparatus for acknowledging and servicing an interrupt issued to a processor, the apparatus comprising:

an external device generating a pulsed interrupt signal;

a first low latency path that couples the external device to an interrupt multiplexing device for transporting the pulsed interrupt signal to the interrupt multiplexing device;

a status bit in the interrupt multiplexing device corresponding to the asserted interrupt and set in response to detecting the pulsed interrupt signal;

a second low latency path for issuing ~~the interrupt~~ to the processor, in response to the pulsed interrupt sinal, a level sensitive interrupt (LSI) signal, the LSI signal remaining asserted until acknowledged by the processor;

an interrupt handler internal to the processor for reading and clearing the status bit over the second low latency path, ~~where~~ whereby ~~clearing~~ the status bit ~~is cleared in response the reading to~~ effectively acknowledges the interrupt and causes the LSI signal to be deasserted.

28. (PREVIOUSLY PRESENTED) The apparatus of claim 27 further comprising:

the interrupt handler checks ownership of a control block and, in response to the processor owning the control block, processes the control block.

29. (PREVIOUSLY PRESENTED) The apparatus of claim 28 further comprising:

a high latency path through which ownership of the control block is assigned.

30. (PREVIOUSLY PRESENTED) The apparatus of claim 28 further comprising:

a current counter incremented in response to each pulsed interrupt signal received at the interrupt multiplexing device;

a last counter incremented in response to each control block processed by the interrupt handler; and

a comparator for comparing the value of the current counter and the value of the last counter and if the value of the current counter is greater than the value of the last counter, which thereby indicates the control block corresponding to the interrupt has not yet been processed.

31. (PREVIOUSLY PRESENTED) The apparatus of Claim 30 further comprising:

circuitry for determining whether a preset limit for processing control blocks has been reached a for dismissing the interrupt handler if the preset limit is reached.

32. (CURRENTLY AMENDED) An apparatus for acknowledging and servicing an interrupt issued to a processor, the apparatus comprising:

means for generating a pulsed interrupt signal at an external device;

means for transporting the pulsed interrupt signal to an interrupt multiplexing device over a first low latency path that couples the external device to the interrupt multiplexing device;

means for asserting a status bit in the interrupt multiplexing device corresponding to the interrupt in response to detecting the pulsed interrupt signal;

means for issuing ~~the interrupt~~ to the processor over a second low latency path, in response to the pulsed interrupt signal, a level sensitive interrupt (LSI) signal, the LSI signal remaining asserted until the interrupt is acknowledged by the processor;

means for reading the status bit over the second low latency path by an interrupt handler internal to the processor; and

means for clearing the status bit in response to the reading of the status bit to effectively acknowledge the interrupt.

33. (CURRENTLY AMENDED) A computer readable media comprising, the computer readable media having instructions written thereon for execution on a processor for:

generating a pulsed interrupt signal at an external device;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a first low latency path that couples the external device to the interrupt multiplexing device;

asserting a status bit in the interrupt multiplexing device corresponding to the interrupt in response to detecting the pulsed interrupt signal;

issuing ~~the interrupt~~ to the processor over a second low latency path, in response to the pulsed interrupt signal, a level sensitive interrupt (LSI) signal, the LSI signal remaining asserted until the interrupt is acknowledged by the processor;;

reading the status bit over the second low latency path by an interrupt handler internal to the processor; and

clearing the status bit in response to the reading of the status bit to effectively acknowledge the interrupt.

34. (CURRENTLY AMENDED) Electromagnetic signals propagating on a computer network comprising,

the electromagnetic signals carrying instructions for execution on a processor for:

generating a pulsed interrupt signal at an external device;

transporting the pulsed interrupt signal to an interrupt multiplexing device over a first low latency path that couples the external device to the interrupt multiplexing device;

asserting a status bit in the interrupt multiplexing device corresponding to the interrupt in response to detecting the pulsed interrupt signal;

issuing ~~the interrupt~~ to the processor over a second low latency path, in response to the pulsed interrupt signal, a level sensitive interrupt (LSI) signal, the LSI signal remaining asserted until the interrupt is acknowledged by the processor;;

reading the status bit over the second low latency path by an interrupt handler internal to the processor; and

clearing the status bit in response to the reading of the status bit to effectively acknowledge the interrupt.

35. (PREVIOUSLY PRESENTED) A method for acknowledging and servicing an interrupt issued to a processor, the method comprising:

generating a interrupt signal at an external device;

transporting the interrupt signal to an interrupt multiplexing device over a first path that couples the external device to the interrupt multiplexing device;

issuing the interrupt to the processor over a second path;

acknowledging the interrupt by the processor performing a read operation on the interrupt multiplexing device over the second path, and without accessing the external device.

36. (PREVIOUSLY PRESENTED) An apparatus for acknowledging and servicing an interrupt issued to a processor, the apparatus comprising:

an external device generating a interrupt signal;

a first path that couples the external device to an interrupt multiplexing device for transporting the interrupt signal to the interrupt multiplexing device;

a second path for issuing the interrupt to the processor;

an interrupt handler internal to the processor for acknowledging the interrupt by accessing the interrupt multiplexing device over the second path and without accessing the external device.

37. (PREVIOUSLY PRESENTED) An apparatus for acknowledging and servicing an interrupt issued to a processor, the apparatus comprising:

means for generating a interrupt signal at an external device;

means for transporting the interrupt signal to an interrupt multiplexing device over a first path that couples the external device to the interrupt multiplexing device;

means for issuing the interrupt to the processor over a second path;

means for acknowledging the interrupt by the processor performing a read operation on the interrupt multiplexing device over the second path, and without accessing the external device.